SAJ H2 & B2S - Compatibility & Max Discharge Power (kW)

Inverter / Battery	B2-12.8-HV1-S	B2-19.2-HV1-S	B2-25.6-HV1-S	B2-32.0-HV1-S	B2-38.4-HV1-S	B2-44.8-HV1-S	B2-51.2-HV1-S	2x B2-25.6-HV1-S	2x B2-32.0-HV1-S	2x B2-38.4-HV1-S	2x B2-44.8-HV1-S	2x B2-51.2-HV1-S
H2-5K-S2	5kW	5kW	5kW	5kW	5kW							
H2-8K-S3	6.4kW	8kW	8kW	8kW	8kW							
H2-10K-S3-A	6.4kW	9.6kW	10kW	10kW	10kW							
H2-10K-T3-AU			10kW	10kW	10kW	10kW	10kW	10kW	10kW	10kW	10kW	10kW
H2-15K-T3-AU			12.8kW	15kW	15kW	15kW	15kW	15kW	15kW	15kW	15kW	15kW
H2-20K-T3-AU			12.8kW	16kW	19.2kW	20kW	20kW	20kW	20kW	20kW	20kW	20kW
H2-25K-T3-AU			12.8kW	16kW	19.2kW	22.4kW	25kW	25kW	25kW	25kW	25kW	25kW
H2-30K-T3-AU			12.8kW	16kW	19.2kW	22.4kW	25.6kW	25.6kW	30kW	30kW	30kW	30kW
Nominal Capacity (kWh)	12.80	19.20	25.60	32.00	38.40	44.80	51.20	51.20	64.00	76.80	89.60	102.40

Note: H2 S2/S3 Single Phase hybrids support 2–6 B2S modules in a single tower. H2 10–30K T3 Three Phase hybrids support 4–8 B2S modules per tower. H2 T3 series supports up to two separate B2S towers via its dual battery inputs. Parallel-connected towers are not currently supported.

Compatible | Compatible - Be mindful that the discharge power is less than inverter AC rating | Not Compatible

Note: H2 S2/S3 Single Phase hybrids support 2–6 B2S modules in a single tower. H2 10–30K T3 Three Phase hybrids support 4–8 B2S modules per tower. H2 T3 series supports up to two separate B2S towers via its dual battery inputs. Parallel-connected towers are not currently supported.