

Fronius Reserva Battery - Compatibility & Rated Discharge Power (kW)



Inverter / Battery	Reserva			
	6.3	9.5	12.6	15.8
Primo GEN24 3.0 Plus	3.0kW	3.0kW	—	—
Primo GEN24 3.6 Plus	3.6kW	3.6kW	—	—
Primo GEN24 4.0 Plus	4.0kW	4.0kW	—	—
Primo GEN24 4.6 Plus	4.5kW	4.6kW	—	—
Primo GEN24 5.0 Plus	4.5kW	5.0kW	—	—
Primo GEN24 6.0 Plus	4.5kW	6.0kW	—	—
Primo GEN24 8.0 Plus	4.5kW	6.75kW	—	—
Primo GEN24 10.0 Plus	4.5kW	6.75kW	—	—
Symo GEN24 5.0 Plus	2.56kW	3.84kW	5.0kW	5.0kW
Symo GEN24 6.0 Plus	4.5kW	6.0kW	6.0kW	6.0kW
Symo GEN24 8.0 Plus	4.5kW	6.75kW	8.0kW	8.0kW
Symo GEN24 10.0 Plus	4.5kW	6.75kW	9.01kW	10.0kW
Symo GEN24 12.0 Plus	4.5kW	6.75kW	9.01kW	11.26kW
Verto Plus 15.0	6.55kW	9.83kW	13.1kW	15.0kW
Verto Plus 20.0	6.55kW	9.83kW	13.1kW	16.38kW
Verto Plus 25.0	6.55kW	9.83kW	13.1kW	16.38kW
Verto Plus 30.0	6.55kW	9.83kW	13.1kW	16.38kW
Verto Plus 33.3	6.55kW	9.83kW	13.1kW	16.38kW

Nominal Capacity (kWh)	1x Stack	6.68	10.03	13.37	16.71
	2x Paralleled Stacks	13.36	20.06	26.74	33.42
	3x Paralleled Stacks	20.04	30.09	40.11	50.13
	4x Paralleled Stacks	26.72	40.12	53.48	66.84



Note: Up to Four equal stacks can be paralleled. Adding stacks increases the capacity only, it does not increase the output power.



Compatible



Compatible - Be mindful that the discharge power is less than inverter AC rating



Not Compatible