

Fronius Reserva Pro Battery - Compatibility & Rated Discharge Power (kW)

Inverter / Battery	Reserva Pro					
	12.0	16.0	20.0	24.0	28.0	32.0
 Primo GEN24 3.0 Plus	3.0kW	3.0kW	3.0kW	—	—	—
 Primo GEN24 3.6 Plus	3.6kW	3.6kW	3.6kW	—	—	—
 Primo GEN24 4.0 Plus	4.0kW	4.0kW	4.0kW	—	—	—
 Primo GEN24 4.6 Plus	4.6kW	4.6kW	4.6kW	—	—	—
 Primo GEN24 5.0 Plus	4.68kW	5.0kW	5.0kW	—	—	—
 Primo GEN24 6.0 Plus	4.68kW	6.0kW	6.0kW	—	—	—
 Primo GEN24 8.0 Plus	4.68kW	6.23kW	7.79kW	—	—	—
 Primo GEN24 10.0 Plus	4.68kW	6.23kW	7.79kW	—	—	—
 Symo GEN24 6.0 Plus	4.68kW	6.0kW	6.0kW	6.0kW	6.0kW	6.0kW
 Symo GEN24 8.0 Plus	4.68kW	6.23kW	7.79kW	8.0kW	8.0kW	8.0kW
 Symo GEN24 10.0 Plus	4.68kW	6.23kW	7.79kW	9.35kW	10.0kW	10.0kW
 Symo GEN24 12.0 Plus	4.68kW	6.23kW	7.79kW	9.35kW	10.91kW	12.0kW
 Verto Plus 15.0	10.63kW	14.17kW	15.0kW	15.0kW	15.0kW	15.0kW
 Verto Plus 20.0	10.63kW	14.17kW	17.71kW	20.0kW	20.0kW	20.0kW
 Verto Plus 25.0	10.63kW	14.17kW	17.71kW	21.25kW	24.79kW	25.0kW
 Verto Plus 30.0	10.63kW	14.17kW	17.71kW	21.25kW	24.79kW	28.34kW
 Verto Plus 33.3	10.63kW	14.17kW	17.71kW	21.25kW	24.79kW	28.34kW

 Nominal Capacity (kWh)	1x Stack	12.00	16.00	20.00	24.00	28.00	32.00
	2x Paralleled Stacks	24.00	32.00	40.00	48.00	56.00	64.00
	3x Paralleled Stacks	36.00	48.00	60.00	72.00	84.00	96.00
	4x Paralleled Stacks	48.00	64.00	80.00	96.00	112.00	128.00



Note: Up to Four equal stacks can be paralleled. Adding stacks increases the capacity only, it does not increase the output power.



Compatible



Compatible - Be mindful that the discharge power is less than inverter AC rating



Not Compatible